




Electrical Test Program - Test (Retractable Trunk Lid Grip)

Test step DTC	Test scope	Test connection	Test condition	Nominal value	Possible cause/Remedy
⇒ 1.0	Rotary tumbler/trunk lid switch (S88/1) Voltage supply	 <p>A37 21 —(—(←(V)→ —(— 18</p>	Disconnect right and left tail lamp connectors. Trunk lid: closed open	>5 V <1 V	Wiring, ⇒ 1.1, PSE control module (A37 or A37/1). Wiring, ⇒ 1.1, A37 or A37/1.
⇒ 1.1	S88/1 Resistance	 <p>A37 21 —(—(←(V)→ —(— 18</p>	Disconnect PSE control module (A37 or A37/1) from  Trunk lid: closed open	>20 kΩ <40 Ω	Wiring, S88/1. Wiring, S88/1.