

Diagnosis – Complaint Related Diagnostic Chart

Complaint/Problem	Possible cause	Test step/Remedy ¹⁾
Complete sound system does not function	Left/right audio power amplifier (N40/3)	23 ⇒ 1.0
Left or right front door speaker group (H4/1 or H4/2) does not function	H4/1 or H4/2 Tuner/amplifier (A2/3) Left/right audio power amplifier (N40/3)	23 ⇒ 2.0
Bass speakers do not function	H4/7 or H4/8	23 ⇒ 3.0
Bass and rear door speakers do not function	Left/right audio power amplifier (N40/3)	23 ⇒ 4.0
Center fill tweeter speaker (H4/11), in mirror base, not functioning	H4/11	23 ⇒ 5.0
Individual speaker does not function	Speaker Left/right audio power amplifier (N40/3)	23 ⇒ 6.0
Fader switch (R26) does not function	R26 Left/right audio power amplifier (N40/3)	23 ⇒ 7.0
Front – rear stereo effect is offset to one side, even with balance/fader adjustments set to mid-range		23 ⇒ 8.0

¹⁾ Observe Preparation for Test, see 22.